

Enclosed Alphanumeric Supplement

Range: 1F100–1F1FF

The Unicode Standard, Version 5.2

This file contains an excerpt from the character code tables and list of character names for *The Unicode Standard, Version 5.2*.

Characters in this chart that are new for The Unicode Standard, Version 5.2 are shown in conjunction with any existing characters. For ease of reference, the new characters have been highlighted in the chart grid and in the names list.

This file will not be updated with errata, or when additional characters are assigned to the Unicode Standard. See <http://www.unicode.org/errata/> for an up-to-date list of errata.

See <http://www.unicode.org/charts/> for access to a complete list of the latest character code charts. See <http://www.unicode.org/charts/PDF/Unicode-5.2/> for charts showing only the characters added in Unicode 5.2. See <http://www.unicode.org/Public/5.2.0/charts/> for a complete archived file of character code charts for Unicode 5.2.

Disclaimer

These charts are provided as the online reference to the character contents of the Unicode Standard, Version 5.2 but do not provide all the information needed to fully support individual scripts using the Unicode Standard. For a complete understanding of the use of the characters contained in this file, please consult the appropriate sections of The Unicode Standard, Version 5.2, online at <http://www.unicode.org/versions/Unicode5.2.0/>, as well as Unicode Standard Annexes #9, #11, #14, #15, #24, #29, #31, #34, #38, #41, #42, and #44, the other Unicode Technical Reports and Standards, and the Unicode Character Database, which are available online.

See <http://www.unicode.org/ucd/> and <http://www.unicode.org/reports/>

A thorough understanding of the information contained in these additional sources is required for a successful implementation.

Fonts

The shapes of the reference glyphs used in these code charts are not prescriptive. Considerable variation is to be expected in actual fonts. The particular fonts used in these charts were provided to the Unicode Consortium by a number of different font designers, who own the rights to the fonts.

See <http://www.unicode.org/charts/fonts.html> for a list.

Terms of Use

You may freely use these code charts for personal or internal business uses only. You may not incorporate them either wholly or in part into any product or publication, or otherwise distribute them without express written permission from the Unicode Consortium. However, you may provide links to these charts.

The fonts and font data used in production of these code charts may NOT be extracted, or used in any other way in any product or publication, without permission or license granted by the typeface owner(s).

The Unicode Consortium is not liable for errors or omissions in this file or the standard itself. Information on characters added to the Unicode Standard since the publication of the most recent version of the Unicode Standard, as well as on characters currently being considered for addition to the Unicode Standard can be found on the Unicode web site.

See <http://www.unicode.org/pending/pending.html> and <http://www.unicode.org/alloc/Pipeline.html>.

Copyright © 1991-2009 Unicode, Inc. All rights reserved.

	1F10	1F11	1F12	1F13	1F14	1F15	1F16	1F17	1F18	1F19	1F1A	1F1B	1F1C	1F1D	1F1E	1F1F
0	0. 1F100	(A) 1F110	(Q) 1F120							DJ 1F190						
1	0, 1F101	(B) 1F111	(R) 1F121	B 1F131												
2	1, 1F102	(C) 1F112	(S) 1F122		S 1F142											
3	2, 1F103	(D) 1F113	(T) 1F123													
4	3, 1F104	(E) 1F114	(U) 1F124													
5	4, 1F105	(F) 1F115	(V) 1F125													
6	5, 1F106	(G) 1F116	(W) 1F126		W 1F146											
7	6, 1F107	(H) 1F117	(X) 1F127			H 1F157										
8	7, 1F108	(I) 1F118	(Y) 1F128													
9	8, 1F109	(J) 1F119	(Z) 1F129					J 1F179								
A	9, 1F10A	(K) 1F11A	(S) 1F12A		HV 1F14A					R 1F18A						
B		(L) 1F11B	(C) 1F12B		MV 1F14B			L 1F17B	IC 1F18B							
C		(M) 1F11C	(R) 1F12C		SD 1F14C			M 1F17C	PA 1F18C							
D		(N) 1F11D	(CD) 1F12D	N 1F13D	SS 1F14D				SA 1F18D							
E		(O) 1F11E	(Wz) 1F12E		PPV 1F14E											
F		(P) 1F11F		P 1F13F		P 1F15F		P 1F17F								

Number with full stop

This symbol completes the set of numbers with full stop starting at U+2488.

1F100 **0.** DIGIT ZERO FULL STOP
≈ 0030 **0** 002E .

Numbers with comma

1F101 **0,** DIGIT ZERO COMMA
≈ 0030 **0** 002C ,

1F102 **1,** DIGIT ONE COMMA
≈ 0031 **1** 002C ,

1F103 **2,** DIGIT TWO COMMA
≈ 0032 **2** 002C ,

1F104 **3,** DIGIT THREE COMMA
≈ 0033 **3** 002C ,

1F105 **4,** DIGIT FOUR COMMA
≈ 0034 **4** 002C ,

1F106 **5,** DIGIT FIVE COMMA
≈ 0035 **5** 002C ,

1F107 **6,** DIGIT SIX COMMA
≈ 0036 **6** 002C ,

1F108 **7,** DIGIT SEVEN COMMA
≈ 0037 **7** 002C ,

1F109 **8,** DIGIT EIGHT COMMA
≈ 0038 **8** 002C ,

1F10A **9,** DIGIT NINE COMMA
≈ 0039 **9** 002C ,

Parenthesized Latin letters

This set provides uppercase versions of the set starting at U+249C.

1F110 **(A)** PARENTHESIZED LATIN CAPITAL LETTER A
≈ 0028 (0041 **A** 0029)

1F111 **(B)** PARENTHESIZED LATIN CAPITAL LETTER B
≈ 0028 (0042 **B** 0029)

1F112 **(C)** PARENTHESIZED LATIN CAPITAL LETTER C
≈ 0028 (0043 **C** 0029)

1F113 **(D)** PARENTHESIZED LATIN CAPITAL LETTER D
≈ 0028 (0044 **D** 0029)

1F114 **(E)** PARENTHESIZED LATIN CAPITAL LETTER E
≈ 0028 (0045 **E** 0029)

1F115 **(F)** PARENTHESIZED LATIN CAPITAL LETTER F
≈ 0028 (0046 **F** 0029)

1F116 **(G)** PARENTHESIZED LATIN CAPITAL LETTER G
≈ 0028 (0047 **G** 0029)

1F117 **(H)** PARENTHESIZED LATIN CAPITAL LETTER H
≈ 0028 (0048 **H** 0029)

1F118 **(I)** PARENTHESIZED LATIN CAPITAL LETTER I
≈ 0028 (0049 **I** 0029)

1F119 **(J)** PARENTHESIZED LATIN CAPITAL LETTER J
≈ 0028 (004A **J** 0029)

1F11A **(K)** PARENTHESIZED LATIN CAPITAL LETTER K
≈ 0028 (004B **K** 0029)

1F11B **(L)** PARENTHESIZED LATIN CAPITAL LETTER L
≈ 0028 (004C **L** 0029)

1F11C **(M)** PARENTHESIZED LATIN CAPITAL LETTER M
≈ 0028 (004D **M** 0029)

1F11D **(N)** PARENTHESIZED LATIN CAPITAL LETTER N
≈ 0028 (004E **N** 0029)

1F11E **(O)** PARENTHESIZED LATIN CAPITAL LETTER O
≈ 0028 (004F **O** 0029)

1F11F **(P)** PARENTHESIZED LATIN CAPITAL LETTER P
≈ 0028 (0050 **P** 0029)

1F120 **(Q)** PARENTHESIZED LATIN CAPITAL LETTER Q
≈ 0028 (0051 **Q** 0029)

1F121 **(R)** PARENTHESIZED LATIN CAPITAL LETTER R
≈ 0028 (0052 **R** 0029)

1F122 **(S)** PARENTHESIZED LATIN CAPITAL LETTER S
≈ 0028 (0053 **S** 0029)

1F123 **(T)** PARENTHESIZED LATIN CAPITAL LETTER T
≈ 0028 (0054 **T** 0029)

1F124 **(U)** PARENTHESIZED LATIN CAPITAL LETTER U
≈ 0028 (0055 **U** 0029)

1F125 **(V)** PARENTHESIZED LATIN CAPITAL LETTER V
≈ 0028 (0056 **V** 0029)

1F126 **(W)** PARENTHESIZED LATIN CAPITAL LETTER W
≈ 0028 (0057 **W** 0029)

1F127 **(X)** PARENTHESIZED LATIN CAPITAL LETTER X
≈ 0028 (0058 **X** 0029)

1F128 **(Y)** PARENTHESIZED LATIN CAPITAL LETTER Y
≈ 0028 (0059 **Y** 0029)

1F129 **(Z)** PARENTHESIZED LATIN CAPITAL LETTER Z
≈ 0028 (005A **Z** 0029)

Latin letter with tortoise shell brackets

1F12A **[S]** TORTOISE SHELL BRACKETED LATIN CAPITAL LETTER S
• used in baseball scoring
≈ 3014 (0053 **S** 3015)

Circled italic Latin letters

1F12B **©** CIRCLED ITALIC LATIN CAPITAL LETTER C
= compact disc, single disc record
≈ <circle> 0043 **C**

1F12C **Ⓜ** CIRCLED ITALIC LATIN CAPITAL LETTER R
= disc record
≈ <circle> 0052 **R**

Circled Latin letter sequences

1F12D **Ⓞ** CIRCLED CD
→ 33C5 cd square cd
≈ <circle> 0043 **C** 0044 **D**

1F12E **Ⓦ** CIRCLED WZ
• from the German term “Warenzeichen”
• indicate a trademarked term without making a legal claim of trademark status
→ 2122 TM trade mark sign
≈ <circle> 0057 **W** 005A **Z**

Squared Latin letters

1F131 **ⓑ** SQUARED LATIN CAPITAL LETTER B
= bank
= b-mode stereo compression broadcasting service (ARIB STD B24)
≈ <square> 0042 **B**

1F132 **ⓓ** <reserved>

1F133 **ⓔ** <reserved>

1F134 **ⓕ** <reserved>

1F135 **ⓖ** <reserved>

1F136 **ⓗ** <reserved>

1F137 **ⓘ** <reserved>



















1F138 **ⓙ** <reserved>

1F139 **ⓚ** <reserved>










1F13A **ⓛ** <reserved>

1F13B **ⓜ** <reserved>

1F13C **ⓝ** <reserved>








1F13D		SQUARED LATIN CAPITAL LETTER N = news (ARIB STD B24) ≈ <square> 004E N
1F13E		<reserved>
1F13F		SQUARED LATIN CAPITAL LETTER P = progressive broadcasting (ARIB STD B24) ≈ <square> 0050 P
1F140		<reserved>
1F141		<reserved>
1F142		SQUARED LATIN CAPITAL LETTER S = stereo broadcasting service (ARIB STD B24) ≈ <square> 0053 S
1F143		<reserved>
1F144		<reserved>
1F145		<reserved>
1F146		SQUARED LATIN CAPITAL LETTER W = wide-format 16:9 broadcasting service (ARIB STD B24) ≈ <square> 0057 W
1F147		<reserved>
1F148		<reserved>
1F149		<reserved>
1F14A		SQUARED HV = hdtv ≈ <square> 0048 H 0056 V
1F14B		SQUARED MV = multi-view television ≈ <square> 004D M 0056 V
1F14C		SQUARED SD = sdtv ≈ <square> 0053 S 0044 D
1F14D		SQUARED SS = surround stereo broadcasting service ≈ <square> 0053 S 0053 S
1F14E		SQUARED PPV = pay-per-view ≈ <square> 0050 P 0050 P 0056 V











White on black circled Latin letters





1F157		NEGATIVE CIRCLED LATIN CAPITAL LETTER H = hotel (ARIB STD B24)
1F158		<reserved>
1F159		<reserved>
1F15A		<reserved>
1F15B		<reserved>
1F15C		<reserved>
1F15D		<reserved>
1F15E		<reserved>
1F15F		NEGATIVE CIRCLED LATIN CAPITAL LETTER P = parking space (ARIB STD B24)

White on black squared Latin letters


The square edges may be slightly rounded.

1F179		NEGATIVE SQUARED LATIN CAPITAL LETTER J = junction (ARIB STD B24)
1F17A		<reserved>
1F17B		NEGATIVE SQUARED LATIN CAPITAL LETTER L = leisure center (ARIB STD B24)
1F17C		NEGATIVE SQUARED LATIN CAPITAL LETTER M = museum, cultural center (ARIB STD B24)
1F17D		<reserved>
1F17E		<reserved>
1F17F		NEGATIVE SQUARED LATIN CAPITAL LETTER P = parking space empty-full (ARIB STD B24)

1F180		<reserved>
1F181		<reserved>
1F182		<reserved>
1F183		<reserved>
1F184		<reserved>
1F185		<reserved>
1F186		<reserved>
1F187		<reserved>
1F188		<reserved>
1F189		<reserved>

1F18A		CROSSED NEGATIVE SQUARED LATIN CAPITAL LETTER P = parking space closed
1F18B		NEGATIVE SQUARED IC = interchange, ramp
1F18C		NEGATIVE SQUARED PA = parking area
1F18D		NEGATIVE SQUARED SA = service area

Squared Latin letter sequences

1F190		SQUARE DJ = disc jockey ≈ <square> 0044 D 004A J
-------	---	---